

DI-300(M) ISDN Router
Copyright (C) 1998 D-Link Corporation. - All Rights Reserved
Last Modify: February 4,1998 by C.C. Chiang

Upload New Firmware file via XMODEM:

1. Enter Main Menu through RS-232 port of DI-300(M) using Terminal Emulator (such as Hyper Terminal of MS-WIN95, PROCOMM Plus, Vterm ...).
2. Enter "24. System Maintenance" then "7. Software Update" and the following message will be displayed.

To update software, system needs to be rebooted.
After system is rebooted, 'Enter Debug Mode' will be displayed.

Please enter 'atur' to upload RAS and ISDN code.
Do you want to continue (y/n):

Please press the "y" key to continue and execut "atur" command after "Enter Debug Mode".

3. After "atur" executed, the message "Now erase flash ROM for uploading ..." will showing.
When message "Starting XMODEM upload....." has appeared, please start to upload(Transfer) the right binary file via XMODEM.

4. When the message "Programming successful...OK" appeared, type "atgo" to reboot.

#