

Quick Installation Guide DES-1008P

8-Port 10/100 Mbps Switch with 4 Port PoE

Check Your Package Contents

These are the items included with your DES-1008P purchase:



DES-1008P
8-Port Fast Ethernet
Switch with 4 Port PoE



CD-ROM
with Product Document



Quick Installation Guide



48V, 1.45A Power
Adapter



Note :

Using a power supply with a different voltage rating will damage and void the warranty of this product.

Notice Before Setting Up the DES-1008P

To setup of the Switch can be performed using the following steps:

- A. Install the DES-1008P in a fairly cool and dry place. See Technical Specification for the acceptable operation temperature and humidity ranges.
- B. Install the Switch in a site free from strong electromagnetic source, vibration, dust, and direct sunlight.
- C. Leave at least 10 cm of space at the left and right hand side of the Switch for ventilation.
- D. Visually inspect the DC power jack and make sure that it is fully secured to the power adapter.



Do not stack any device on top of the Switch.

Connecting the DES-1008P Fast Ethernet Switch with 4 Port PoE to Your Network



A. Power:

Power is supplied through an external DC power adapter. Since the switch does not include a power switch, plugging its power adapter into a power outlet will immediately power it on.


B. Fast Ethernet Ports (Port 1~8):

These ports support network speeds of either 10 Mbps or 100 Mbps, and can operate in half- and full- duplex transfer modes. These ports also support automatic MDI/MDIX crossover detection, which gives the Switch true, “plug and play” capabilities. Just connect any network cable between the Switch and the device, and The Switch will automatically detect the settings of the device and adjust itself accordingly.

C. PoE Ports (Port 1~4 only):

These ports are PoE Enabled ports, the PoE port will automatically activate when a compatible terminal is identified. The Switch will supply power through the Ethernet port to the connected PoE device. For legacy devices that are not compatible, the PoE port will not offer the power to this device. This feature allows users to freely and safely mix legacy and PoE compatible devices on the network.

LED Indicators



The LED Indicators will allow you to monitor, diagnose and troubleshoot any potential problem with the switch, connection or attached devices.

A. System Power:

This indicator lights green when the Switch is receiving power, otherwise, it is off.

B. Link / Act:

This indicator lights green when a port is connected to a 10/100 Mbps station successfully and has a good link. A blinking green indicator means that a port is transmitting or receiving data on the network.

C. 100M Speed:

This LED indicator lights green when the port is connected to a 100 Mbps Fast Ethernet station. The indicator lights off when the port is connected to a 10 Mbps Ethernet station or no link.

D. PoE MAX:

Off: At least 10W of PoE power is available to connect another PoE device.

Green: When the power output to powered devices has reached or exceeded the maximum power budget. No additional powered devices connected will be powered.

Blinking Green: Indicates at least 10W of PoE power is available again.

E. PoE Status:

Green : When the PoE powered device is connected and the port supplies power successfully.

Red : When the PoE port has failed, possibly due to

1. PoE power circuit shortage
2. Power over current: over the power current of powered device's classification
3. Out of PoE voltage of 44 ~ 57 VDC output

Off : No PoE powered device connected.

Technical Support

Thank you for choosing D-Link products. For further information, support, product drivers and manuals please visit the D-Link website at www.dlink.eu