

Document Title: How to Use HyperTerminal to Firmware Update DI-701

Question:

How to use HyperTerminal to update firmware?

Answer:

1. Connect the DI-701 and Com2 (or Com1) using RS232 port.
2. HyperTerm: 38400, 8, n, 1, flow Control=None.
3. Reboot the DI-701. When doing the RAM test, press "Esc" key many times, and it will go to BIOS> mode.
4. In BIOS> mode, type " f "
5. HyperTerm -> Transfer -> Send file -> firmware.bin (XMODEM).
6. Enter "r" to reboot.