

Product Highlights

Get Connected Anywhere

Provides high-speed connectivity in areas without Wi-Fi for blazing-fast Internet access when you're on the road

Super-Fast 4G LTE Connectivity

Access the Internet using 4G LTE with download speed of up to 150 Mbps

Travel-friendly Design

Pocket-sized with no batteries or cables, making it easy to take with you when you're traveling or simply on-the-go



DWM-222

4G LTE USB Adapter

Features

Connectivity

- Works with Windows and Mac OS-based computers or notebooks with USB port²
- SIM slot (6-pin) allows you to access the Internet using your mobile service
- microSD card reader gives another portable storage option on-the-go
- Integrated antenna keeps a small footprint for true portability

Mobile Connections

- LTE/DC-HSPA+/HSPA/WCDMA support for the latest in mobile network technology
- GSM/GPRS/EDGE support for legacy mobile plans and fallback in the absence of a 4G LTE signal
- Data rates of up to 150 Mbps downlink and 50 Mbps uplink¹

Software

- Connection Manager software gives you access to your SIM card's phonebook and SMS messaging

Easy Setup

- Built-in drivers and software mean that no CD-ROM drive is required
- LED indicator let you know the status of your connection instantly
- One piece design to simplify usage and travel

The DWM-222 4G LTE USB Adapter is a portable travel modem that allows you to connect to the Internet wherever you are¹. With fast downlink and uplink data rates, as well as low latency, it provides you with a high-performance and responsive connection when you're on the road.

Breakthrough Speeds with 4G LTE Technology

The DWM-222 4G LTE USB Adapter gives you high-speed access to the Internet wherever you are. Using super-fast 4G LTE technology, you can achieve downlink speeds of up to 150 Mbps and uplink speeds of up to 50 Mbps¹ so you don't have to slow down when you're on the move.

Your Mobile Internet Service, Anywhere

Simply plug the 4G LTE USB Adapter into your computer and get Internet access anywhere you can receive an LTE as well as backward compatibility with HSPA, GSM, GPRS, or EDGE data signal. The DWM-222 also has an integrated antenna for a connection that is consistent and reliable whether you're in a café, a business lunch, or even a concert.

Simple to Set Up with Built-in Software

The DWM-222 is plug and play² with drivers built right into the modem, making installation both fast and simple. It can be used on notebooks and netbooks without a CD-ROM drive; simply plug it into a USB port and the drivers install automatically, getting you up and running in no time. Additional Connection Manager software is also built-in, so you can send and receive SMS messages without downloading additional software.

Designed for True Portability

The DWM-222 4G LTE USB Adapter is small and slim enough to carry around in your purse or pocket. It features a microSD card reader for optional removable storage (up to 32 GB), allowing you to always have your files and contacts on hand. With no batteries, cables, or additional hardware required, you can truly take it with you wherever you go.

Technical Specifications

General

Device Interfaces	<ul style="list-style-type: none"> • USB 2.0 • SIM slot (6-pin) 	<ul style="list-style-type: none"> • microSD card slot (microSD card not included, supports up to 32 GB)
Broadband Wireless Support	<ul style="list-style-type: none"> • LTE/DC-HSPA+/HSPA/WCDMA 	<ul style="list-style-type: none"> • GSM/GPRS/EDGE
Radio Frequency Bands	<ul style="list-style-type: none"> • LTE @ 2600/1800/800 Mhz • UMTS @ 2100/900 Mhz 	<ul style="list-style-type: none"> • Quadband GSM/GPRS/EDGE
Data Rates ¹	<ul style="list-style-type: none"> • LTE: 3GPP Rel-9 FDD-LTE Cat.4 • Downlink: Up to 150 Mbps • Uplink: Up to 50 Mbps 	<ul style="list-style-type: none"> • DC-HSPA+ • Downlink: Up to 42 Mbps • Uplink: Up to 5.76 Mbps
Bandwidth	<ul style="list-style-type: none"> • 1.4, 3, 5, 10, 15, 20 MHz 	
Minimum System Requirements	<ul style="list-style-type: none"> • Windows XP/Vista/7/8, Mac OS X 10.5 or higher • 128 MB RAM or greater 	<ul style="list-style-type: none"> • 50 MB available disk space

Functionality

LTE Output Power	<ul style="list-style-type: none"> • Class 3 (23 dBm) 	
Antenna	<ul style="list-style-type: none"> • Integrated antenna 	
Status LED	<ul style="list-style-type: none"> • Green (blinking): Connected to LTE network • Blue (blinking): Connected to 3G network 	<ul style="list-style-type: none"> • Purple (blinking): Connected to 2G network • Red (blinking): No service/device error
Plug and Play	<ul style="list-style-type: none"> • Built-in drivers and software; no CD-ROM required 	
Software Features	<ul style="list-style-type: none"> • Connection Manager • Phonebook 	<ul style="list-style-type: none"> • SMS messaging • APN Manager

Physical

Dimensions	<ul style="list-style-type: none"> • 103 x 34 x 11.5 mm (4.06 x 1.34 x 0.45 inches) 	
Weight	<ul style="list-style-type: none"> • 33 grams (1.16 ounces) 	
Certifications	<ul style="list-style-type: none"> • CE • Body SAR (DAS): 1.13 W/kg 	<ul style="list-style-type: none"> • WHQL • RoHS

¹ Data rates are theoretical. Data transfer rate depends on network capacity and signal strength. Please check regional mobile operators for 4G LTE/3G mobile Internet availability.

² Compatible with Windows XP/Vista/7/8, Mac OS X 10.5 or higher



For more information: www.dlink.com

D-Link European Headquarters. D-Link (Europe) Ltd., First Floor, Artemis Building, Odyssey Business Park, West End Road, South Ruislip HA4 6QE, United Kingdom. Specifications are subject to change without notice. D-Link is a registered trademark of D-Link Corporation and its overseas subsidiaries. All other trademarks belong to their respective owners. ©2020 D-Link Corporation. All rights reserved. E&OE.

Updated July 2020

D-Link[®]