



# **3-Port Print Server**

The DP-300U multi-port print server is designed to share a cluster of printers located at a central site such as a data center or a computer room. It is equipped with 2 parallel printer ports and 1 USB port, allowing 2 parallel printers and 1 USB printer to be shared over the network. Supporting multiple network operating systems, this device brings a high level of flexibility and performance to your office printing needs.

### Multiple Ports Save Cost

With 3 printer ports available from a single device, you don't need to purchase and install a separate print server for each printer. This multi-port print server is only slightly more expensive than a single-port print server. Where your printers are closely placed together, it makes sense to buy a single print server instead of three. Each of your printers is connected to a printer port on the server through a printer cable.

# Simultaneous Printing on All Printers

Equipped with a powerful CPU, large memory and high-speed printer ports, this print server makes printing of your network files fast. All printers attached to this device can print their print jobs at the same time, giving your multi-port print server a similar performance as that of 3 separate single-port print servers.

# Multiple Network OS Support

The DP-300U supports as many network OS as these: Windows 95, 98, ME, NT 4.0, XP, Apple MacOS with AppleTalk, Linux, Solaris, SCO Unix, IBM AIX and NetWare 5.x native NDS. Better yet, you can configure different OS on different printers and have them print at the same time. This gives you all the flexibility when you select the DP-300U.

# **Bi-directional Printer Communication**

HP PJL protocol is supported for bi-directional network printer communication, providing you with critical information about the network printer.

# **Key Features**

- 2 parallel printer ports, 1 USB 1.1 port supporting USB printer
- Multiple printer ports ideal to share out cluster of printers
- Auto-sensing 10/100Mbps Fast Ethernet port easily connects to network
- Windows-based administrative program for easy setup/management of print jobs
- Bi-directional communication to collect and report information/status of attached printers
- Large flash memory with easy software upgrade
- SNMP and MIB-II (RFC 1213) support for platformindependent management
- Easy web-based configuration from any browser

# **Technical Specifications**

#### **Printer Ports**

- 2 DB-25 IEEE 1284 bi-directional parallel ports
- 1 USB 1.1 port

#### **LAN Port**

RJ-45 10/100Mbps auto-sensing 10BASE-T/100BASE-TX port

#### **Parallel Port Bi-directional Communication**

Hewlett-Packard PJL (Printer Job Language) support

#### **Network Protocols**

- $\hbox{-} Transport\ Protocols:\ TCP/IP,\ NetBEUI,\ AppleTalk/EtherTalk}$
- TCP/IP Protocols: BOOTP, SNMP, Telnet, TFTP, FTP, LPD, RARP, DHCP

#### **Management and Diagnostics**

Standard: SNMP

MIBs: MIB-II (RFC 1213)

#### Configuration Reset

Reset button

# Flash memory

512K Bytes

#### **Diagnostic LED Indicators**

- Power
- Link/Act
- USB
- LPT1
- LPT2

## **OS Support**

- Windows 95, 98, ME, NT 4.0, XP
- Apple MacOS with AppleTalk
- Linux
- Solaris
- SCO Unix
- IBM AIX
- NetWare 5.x native NDS

## **Environmental & Physical**

# **Input Power**

- 5V DC/ 2.5A
- Through external power adapter

## **Dimensions**

193 mm (W) x 117 mm (D) x 34mm (H)

# Weight

Approx. 300 grams

#### **Operating Temperature**

0°C to 50 °C

#### **Storage Temperature**

-25 to 55°C

#### Humidity

5% to 95% non-condensing

### **Emissions**

- FCC Class B
- CE Class B
- C-Tick
- UL
- LVD (EN60950)

# **Box Includes**

- DP-300U device
- CD-ROM with Manual and Print Server Administration program
- Ouick Installation Guide
- External power adapter

# **Print Server**









# Ordering Information

### 3-Port Print Server

DP-300U 2 parallel printer ports, 1 USB 1.1 port

# Please specify your order as follows:

DP-300U/A With US standard power adapter DP-300U/B With UK standard power adapter DP-300U/E With EU standard power adapter DP-300U/CN With China standard power adapter DP-300U/N With Australia standard power adapter



D-Link is a registered trademark of D-Link Corporation/D-Link System Inc. All other

Europe France Benelux Italy Iberia Sweden Norway Finland Singapore **Australia** Japan India Middle East Turkey Chile Brasil South Africa Russia

D-Link Corp.

TEL: 1-905-8295033 TEL: 44-20-8731-5555 TEL: 49-6196-77990 TEL: 33-1-30238688 TEL: 31-40-2668713 TEL: 39-2-2900-0676 TEL: 34-93-4090770 TEL: 46-(0)8564-61900 TEL: 47-22-991890 TEL: 45-43-969040 TEL: 358-9-2707-5080 TEL: 65-6774-6233 TEL: 61-2-8899-1800 TEL: 81-3-5434-9678 TEL: 86-10-8518-2533 TEL: 91-22-652-6696 TEL: 9714-8834234 TEL: 90-212-335-2553 TEL: 56-2-232-3185 TEL: 55-11-3094-2910 TEL: 27(0)1266-52165 TEL: 7-095-737-3389 TEL: 886-2-2910-2626

TEL: 1-949-788-0805

FAX: 1-905-8295095 FAX: 44-20-8731-5511 FAX: 49-6196-7799300 FAX: 33-1-30238689 FAX: 31-40-2668666 FAX: 39-2-2900-1723 FAX: 34-93-4910795 FAX: 46-(0)8564-61901 FAX: 47-22-205700 FAX: 45-43-424347 FAX: 358-9-2707-5081 FAX: 65-6774-6322 FAX: 61-2-8899-1868 FAX: 81-3-5434-9868 FAX: 86-10-8518-2250 FAX: 91-22-652-8914 FAX: 9714-8834394 FAX:90-212-335-2500 FAX: 56-2-232-0923 FAX: 55-11-3094-2921 FAX: 27(0)1266-52186 FAX: 7-095-737-3390 FAX: 886-2-2910-1515 TEL: 886-2-2916-1600 FAX: 886-2-2914-6299

FAX: 1-949-753-7033



Rev. 01 (Mar. 2003) Printed in Taiwan