

14

D-Link DWL-R60AT Indoor Directional Antenna



Remove one default antenna from the wireless device and start to assemble!



D-Link's Single Patch Flat Antenna offers the most cost effective solution for extending the wireless LAN coverage area. The antenna is fully compatible with all products and can be used with any 2.40 to 2.4835 GHz products.

Installation:

1. Remove the original antenna from your wireless device.
2. Screw the DWL-R60AT RP- SMA connector into your wireless device.
3. Adjust the antenna to the suitable direction for extending the wireless coverage area.

Frequency band	2400-2500MHz
Antenna gain	6.0dBi Typical
VSWR	2.0:1 Max.
Polarization	Linear
HPBW / H-plane	90°
HPBW / E-plane	75°
Impedence	50 Ohms nominal
Dimensions HxWxD	80x85x12.8 mm
Weight	75gw

Package Contents:

- DWL-R60AT Antenna
- Quick Installation Guide